



www.ipc-markt.de

42" High Bright Tageslicht TFT HB-4225 -SLO

SLO4225

42" Open Frame LCD Display, LED Backlight, 1000nits,FHD(1920x1080)

42" Open Frame LCD panel, built-in 1000 nits high bright for sunlight readable LCD display, high transmittance color filter, high transmission polarizing plates, Low Power Consumption, suitable for kiosk, Digital Signage, gaming, studio display, gas pump.

Key Features

- Sunlight Readable
- LED Backlight
- Full HD(1920x1080)
- High Shock & Vibration Resistance
- Low Power Consumption
- High Uniformity
- Low EMI Noise
- Wide Dimming
- Life Expectancy
- Wide Viewing Angle



Specifications

Preliminary

| | |
|--------------------------------------|--|
| Model No. | SLO4225 |
| Description | 42" Open Frame LCD Display, LED Backlight, 1000nits, FHD(1920x1080) |
| Display Area (mm) | 930.24 x 523.26mm |
| Brightness | 1000 cd/m ² |
| Resolution | 1920x1080 (FHD) |
| Contrast Ratio | 3000 : 1 |
| Pixel Pitch (mm) | 0.1615 (H) x 0.4845 (V) |
| Viewing Angle | +88°~-88°(H), +88°~-88°(V) |
| Display Colors | 16.7M |
| Response Time (Typical) | 8.5ms |
| Power Consumption | 162W |
| Dimensions (mm) | 971.5x620x61.73mm |
| Weight (Net) | 22.5Kg |
| LED Driving Board | LID42C01 |
| Control Board (Optional) | <input type="checkbox"/> AD5621GA <input type="checkbox"/> AD5621GD <input type="checkbox"/> AD5766GDVA <input type="checkbox"/> AD2662GDVAR |
| <input type="checkbox"/> AD5621GA | VGA+Audio |
| <input type="checkbox"/> AD5621GD | VGA+DVI |
| <input type="checkbox"/> AD5766GDVA | VGA+CVBS+S-Video+Audio (Optional DVI / Component) |
| <input type="checkbox"/> AD2662GDVAR | VGA+DVI (Optional S-Video/ Component / Audio) |
| F / R Control Button | <input type="checkbox"/> 5 Key <input type="checkbox"/> 4 Key |
| <input type="checkbox"/> 5 Key | Power Switch, Menu, Select (+,-), Auto |
| <input type="checkbox"/> 4 Key | Power Switch, Menu, Select (+,-), |
| OSD Menu | Brightness, Contrast, H/V Position, Color, Phase, Clock... |
| Optional | <input type="checkbox"/> AOT <input type="checkbox"/> Touch Screen |